



Model LVD-15

Low Voltage Detector



CE

The non-contact Voltage Detector is intended to check for the presence of AC Voltage, signaling the user with an intermittent tone and a flashing LED.

The LVD-15 is used to detect voltage in outlets, lighting fixtures, circuit breakers, wires, and cables or to find a break in a wire.

Features

- Bright LED and audible alarm sound when voltage is present.
- Designed for non-contact voltage detection.
- Can be used to find a break in a wire.
- Flashlight function.
- ON/OFF switch for longer battery life.

Specifications

Voltage detection	50V~1000V AC
Frequency	50~500 Hz
Measurement category	CAT III 600V
Indication	LED and Tone
Operating conditions	Temperature : 0~40°C Humidity : Less than 80% R.H.
Altitude	2000m maximum
For indoor use only	√
Pollution degree	2
Dimensions	142(L) × 28(W) × 27(D)mm
Weight (battery included)	Approx. 45g
Power source	1.5V (AAA) × 2
Safety standard	EN 61010-1 CAT III 600V EN 61326-1

