



# Model 863 PR

## Phase Sequence Indicator

### 863 PR Phase Sequence Indicator (Contact Type)



CE

#### Features

- Two functions in one unit: open phase and phase sequence detection.
- Neon light indicators.
- Large size alligator clips for easy clipping onto switch-boards terminals.
- Allows you to check a wide range of 3-phase power sources.
- Special test leads length are available on request.

#### Specifications

Input voltage	100-500V AC
Frequency range	45 - 70 Hz
Circuit structure	All electronic (not mechanical)
AC power consumption	Approx. 7mA
Dimensions	102(L) × 78(W) × 32.5(D)mm
Weight.	Approx. 228g
Safety standard	EN 61010-1 CAT III 600V EN 61326-1



CAC-860 B

#### Accessories

Instruction manual  
Soft pouch